

Data Sheet



Arteor™

Electronic Push Button Dimmer, All Load,
3 Wire, 400VA

CAT NO. AR400A3PMWE, AR400A3PMMGN



Cat No.	AR400A3PMWE, AR400A3PMMGN
Description	Electronic Push Button Dimmer, All Load, 3 Wire, 400VA
Supply voltage	230 - 240V a.c.
Frequency	50Hz
Maximum load	400VA
Minimum load	0VA
Derating	Refer to derating chart on instruction sheet
Operating temperature	0 to 50°C
Humidity	10 to 90% RH (Non-condensing)
Colour	White (WE), Magnesium (MGN)
Compliance	AS/NZS 3100
Dimensions (W x H x D)	21 x 21 x 41mm

Arteor™

Electronic Push Button Dimmer, All Load, 3 Wire, 400VA

CAT NO. **AR400A3PMWE, AR400A3PMMGN**



Single product	
Cat No.	Barcode
AR400A3PMWE	9321001419471
AR400A3PMMGN	9321001419501

Inner box (QTY 10)		
Cat No.	Barcode	Dimensions (WxHxD)
AR400A3PMWE	9321001419488	126 x 162 x 83mm
AR400A3PMMGN	9321001419518	126 x 162 x 83mm

Outer box (QTY 120)		
Cat No.	Barcode	Dimensions (WxHxD)
AR400A3PMWE	9321001419495	330 x 250 x 80mm
AR400A3PMMGN	9321001419525	330 x 250 x 80mm

- Suitable for all loads (including LED *)
- 3 Wire technology soft touch electronic push button
- Multi-way dimming option (Secondary Dimmer Cat No. AR450SM series)
- Programmable LED indicator
- Programmable Soft Start mode, Max/Min light levels
- Dimming level memory function
- Short circuit and overload protection
- KickStart™ mode suitable for modern light sources
- Program parameters stored in a non-volatile memory
- Complies to Australian Standards AS/NZS 3100

*This product doesn't work with all dimmable LED's and should be bench tested prior to installation.

HPM Legrand - AUS
1300 369 777
www.legrand.com.au
ABN 31 000 102 661

HPM Legrand - NZ
0800 476 009
www.legrand.co.nz

Refer to your group buying office, HPM Legrand Sales Representative or HPM Legrand Sales Office for pricing.

Please note: specifications are subject to change without prior notice.